



## MPR-2 Series New Generation Network Analyzers

MPR-2 Series **DIN type** network analyzers are designed for detailed measurement and analysis of electrical parameters. Real-time monitoring is supported via **LCD screen**.

Thanks to **the communication feature** of devices, energy measurements can be monitored from a single monitoring center.

MPR-2 series can detect the status of devices in the field with digital inputs and provide control of devices (breakers, switches, contacts, etc.) with digital outputs and relays.

- DIN rail mounting
- 2.1" segment LCD screen
- 256 event record
- 4 MB memory and LOG record
- Detailed measurement up to 51 harmonics
- Current & voltage unbalanced measurement
- Detection of connection errors
- Compatible with **plug&meter** current transformers



# SPECIFICATIONS

	MPR-24	MPR-255-22	MPR-265-21	MPR-275-23	MPR-265-21-PM	MPR-245-PM	MPR-24-PM
<b>ENCLOSURE</b>							
Dimensions	DIN4 Rail Mounting						
Protection Class	Terminals: IP20, Front: IP40						
Display	2,1" Segment LCD						
<b>MEASUREMENT</b>							
<b>Voltage</b>							
Measurement Range	10-300 VAC (L-N), 10-480 VAC (L-L)						
Measurement Range with Voltage Transformer	10 V - 999,9 kV						
Accuracy	0,5% ± 1 Digit						
Input Impedance	> 1 MΩ						
Burden	< 0,5 VA						
<b>Current</b>							
Nominal Current	In: 5A / 1A						
Minimum Current	5 mA						
Measurement Range	50 mA - 5,5 A						
Measurement Range with Current Transformer	50 mA - 10.000 A						
Accuracy	0,5% ± 1 Digit						
Burden	< 1 VA						
Overload Current	1,2 x In						
Short Time Overload (1 sec)	10 x In						
<b>Power / Energy</b>							
Active Power	0 - 1 GW ; 1% ± 1 Digit						
Reactive Power	0 - 1 GVAR ; 2% ± 1 Digit						
Apparent Power	0 - 1 GVA ; 1% ± 1 Digit						
Power Factor	± 1.00 ; Accuracy ± 0,02						
Active Energy	0 - 99 999 999 kWh or MWh; Accuracy 1% (Class 1)						
Reactive Energy	0 - 99 999 999 kVarh or MVarh; Accuracy 2% (Class 2)						
Apparent Energy	0 - 99 999 999 kVAh or MVAh; Accuracy 1% (Class 1)						
Tariff	-	8					-
Total Harmonic Distortion	-	L - L Voltage (%THD-U); L - N Voltage (%THD-V); Current (%THD-I)					-
Individual Harmonics	-	2-51 Voltage (V) and Current (I)					-
Voltage and Current Unbalances	-	•					-
Demand Period	1,5,10,15,20,30,60 min						
Frequency	45-65 Hz						
Sampling Rate per Period	128						
<b>SUPPLY</b>							
Operating Voltage	95-270 VAC/DC (12-50 VDC for MPR-2X-D series)						
Operating Frequency	50/60 Hz						
Power Consumption	< 6 VA						
<b>COMMUNICATION</b>							
Interface / Protocol	-	RS 485 / Modbus RTU					-
Transfer Rate	-	2400 - 115200 bps					-
<b>MEMORY</b>							
Internal Memory Size	-	4 MB					-
<b>INPUTS and OUTPUTS</b>							
<b>Digital Input</b>							
Pulse Width	-	20 - 500 ms					-
Operating Voltage	-	5...30 VAC/DC					-
Switching Current	-	max 50 mA					-
<b>Digital Output</b>							
Supply Voltage	-	5-30 VDC (Open Collector)	-	5-30 VDC (Open Collector)	-	-	
Pulse Width	-	20 - 1000 ms	-	20 - 1000 ms	-	-	
Pulse Duty	-	20 - 1000 ms	-	20 - 1000 ms	-	-	
<b>Relay Output</b>							
Relay Output	-	1 NO, 250 VAC / 5 A		-	1 NO, 250 VAC / 5 A		-
<b>Analog Output</b>							
Current Output	-	-		0 - 20 mA, 4 - 20 mA, 0 - 24 mA	-		
Voltage Output	-	-		0 - 5 V, 0 - 10 V, ± 5 V, ± 10 V	-		
<b>CONNECTIONS</b>							
Mounting Type	Rail Mounting						
Connection Terminals	Screw terminal with socket						
Connection Types	3P4W, 3P3W, 3 Phase Aron, 3P4W (balanced), 3P3W (balanced)						
<b>AMBIENT CONDITIONS</b>							
Ambient Temperature	-10 / + 70°C						
Storage Temperature	-20 / + 80°C						
Overvoltage Category	III						
Pollution Degree	II						
Maximum Ambient Humidity	90%						
<b>STANDARDS</b>							
Standards	EN 61557-12, EN 61326-1, EN 61000-6-2, EN 61000-6-4, EN 62053, EN 60068, EN 61010						

Compatible with x/333 mV and ENTES meter current transformers.

## HEADQUARTERS

Address: Dudullu OSB; 1. Cadde; No: 23 34776 Umraniye - ISTANBUL / TURKIYE Tel: +90 216 313 01 10 Fax: +90 216 314 16 15 Sales Fax: +90 216 365 71 71

E-mail: contact@entes.eu Web: www.entes.eu Coordinates: 40,995852 N, 29,178398 E

## INTERNATIONAL BRANCH OFFICES

ISTANBUL : contact@entes.eu Tel: +90 216 313 01 10 Fax: +90 216 314 16 15

INDIA : contact@entes.in Tel: +91 981 - 2980004

GREECE : contact@entes.eu Tel: +30 2310 706999 +30 2310 707296

GERMANY : kontakt@enteselektronik.com Tel: +49(0) 7022-931992-0

© ENTES Elektronik Cihazlar İmalat ve Ticaret A.Ş.

